TECHNICAL DATA

S286 Oil Level Switch – **Capacitance** Type





9-36 VDC.

The S286 is an active device designed to give an alarm signal if liquid falls below, or rises above, a preset level. It can be specified with a delay to eliminate false alarms due to turbulence.

Containing a factory programmable microprocessor, the switch offers sink to ground or source voltage output. Its small footprint with limited intrusion into the tank means a reduced risk of damage and a wide range of customer specifiable options make it suitable for most applications.

For high accuracy the S286 is ideally mounted horizontally at the point where an alarm or control signal is required. However, the switch can be mounted vertically - contact Fozmula with your application requirements.

SPECIFICATION

Mineral oils, typically used in engines or hydraulic actuators, compatible with brass, PTFE and FVMQ.

Liquid types: **Electrical rating**

Supply voltage: Supply current: Max. load current: Alarm delay time:

Connection:

Power up delay: Power up state: Output type: Output pin: Output state:

Connections: Environmental Ratings

Ingress:

Max. pressure: Temp. range: Weight: EMC:

7 mA + source output. 1.0 A (sink) or 20 mA (source). 0 to 25 s rising or falling (factory set). 4 way Delphi Packard Metri-Pack 150 series connector. 0 to 10 s (factory set). 'In Liquid' or 'Out of Liquid' (factory set). Sink (open collector) and/or Source (supply voltage). Pin D (sink) or Pin A (source). Sink Open / Closed in liquid (factory set). Source On / Off in liquid (factory set). See diagram below.

IP67 (with mating connector fitted).

70 g typical (dependent on thread size)


Construction Body: Probe: Terminals[.] Seals: Connector:

Brass. PTFE. Brass. Tin Plated. FVMQ. PA66 30% Glass Filled Nylon.

Vibration (15.3 Grms)

3 orthogonal planes for 3 hours per plane Testing performed in accordance with BSEN 60068-2-64:1993 Drop: 1 m to concrete surface.

S286



5.0 Bar (72 psi)

ISO13766:2006

-40 °C to +125 °C


1/2" BSPT


BSP1

R

ecommended Installation Tightening Torques			
1⁄4" NPTF	9 Nm	M14x1.5	10 Nm
¾" NPTF	11 Nm	M18x1.5	15 Nm
1⁄2" NPTF	20 Nm		
1/ " BODD	15 Nm		

20 Nm





TYPICAL APPLICATION

NOTE: IF SINK ONLY OUTPUT IS REQUIRED THEN PIN A IS NOT USED.

Optional accessories

C/K1: Packard Metri-Pack 150 series mating connector kit to suit harness wire cross sectional area of 0.8 to 1.0 mm² and sleeve Ø1.60 to 2.15 mm.

Hermes Close | Tachbrook Park | Warwick | CV34 6UF | United Kingdom Tel: +44 (0)1926 466700 | Fax: +44 (0)1926 450473 | sales@fozmula.com

E. & O. E. © Fozmula Limited.

www.fozmula.com

JP 29-Mar-17 3.9 rev 1 Since the suitability of these products depends upon a wide range of factors not in our control, Fozmula Limited expects and understands that you will conduct the testing and evaluation necessary to determine that these products are suitable for your application. Whilst every effort is made to ensure the above details are correct at the time of printing, Fozmula Limited reserves the right to make material changes, and or technical changes without notification.